

## USER Instructions for PP-WATTMETER-BUDGET

### Features

This is a multifunction compact & light weight watt meter.

It has a battery voltage alarm function and can be directly installed in your model to measure real-time current, voltage and watts.

It can also record the maximum current, and watts along with the minimum voltage.

### Specifications

- Operating voltage range: 5.6V-30V
- Current measuring range: 0.1A-100A
- Current accuracy: 0.1A
- Alarm voltage setting range: 5.6V-25V
- Alarm Voltage Setting step: 0.1V
- Size: 75 x 30 x 10mm
- Weight: 19g

### LED State And Operating Instructions

·All LED's off. The watt meter displays scrolling voltage, current, and power values.

·AMP LED on. Displays real-time battery current in Amps.

·WATT LED on. Displays real-time battery output power in Watts.

·VOLT LED on. Displays real-time battery voltage.

·PEAK LED on. Displays scrolling maximum current, maximum Watts and minimum voltage.

·All LED's flashing at the same time. Indicates the users battery alarm.

### Key Operation

·Press button, the watt meter will scroll between the above states;

·Press button for more than 3 seconds in any state, then release the button when all LED light, the power meter goes into alarm voltage setting state and can set the alarm voltage from 5.6V-25V with 0.1V step.

